

Cable not included!



## SUPRA MAINS BLOCK MD-BE SPC BLACK

Screened Mains block with NIF-filter & silver plated OFC internal wiring

Rev.date: 2023-01-13

Customs tariff no: 8536901000

Country of origin: Sweden

### SUPRA Mains Block MD-BE Silver Edition

Supra LoRad MD mains blocks are designed to shield and filter noise. Supra NIF (Non-Intrusive Filtering), an efficient high frequency (RFI) transient filter. It is designed and configured to efficiently suppress RFI interference, but not to dampen quick recharge demands from the connected devices power supplies. Supra NIF is developed by Ben Duncan Research in England.sources. It is possible to order with custom configuration and have a capacity to suppress noise floor up to 40 dB!

Switch (optional), include also a high current in-rush capable on/off switch allowing for turning the entire equipment on or off.



All parts are made in Sweden or Germany & assambled in our factory in Ljungskile, Sweden.

- Noise damping up to 40 dB!
- Internal wiring of 2.5 mm<sup>2</sup> silver plated oxygen-free copper leads
- Support a staggering peak power 2400 Watt @ 230 Volt and 10 Ampere
- Protect both you and your gear from various alternating fields
- Wall mounted or standing on a flat hard surface. Rubber feet and brackets included
- Custom tailored NIF-filter from Ben Duncan Research in UK
- Shielded aluminum chassis prevents electric, electro-magnetic and magnetic fields



Outlet with earth pin



### CONSTRUCTION

Chassis:	Aluminum, black
Standard:	Belgian/French Standard
Inlet socket:	SUPRA MCH-10, 10A
Outlet sockets:	6 x SUPRA MCH-16/BE Schuko
Rated Current/Voltage:	10A / 250V / 2400W
Max RFI Noise damping:	40dB
Fuse:	Ceramic 10A, slow
Width & height (WxH):	90x50mm
Length (L):	MD06-BE = 378mm + 52mm for each additional socket
Standard filtering:	No filter on outlet no 1 for MD02-MD06 Increased filtering, the last socket got highest damping



All mains blocks can be ordered with or without filters for any of the sockets. Power Amps are recommended to be connected to an unfiltered outlet.

Connect the Mains block with a LoRad cord set (10A) further reduce noise by 6-12 dB!



PRODUCT	Qty	Part no.	EAN-13	Carton	Weight
MAINS BLOCK MD06-BE SPC BLACK	1pc	3024000758	7330060207792	20	1,2kg