



## SUPRA MAINS BLOCK MD-16-EU

Screened Mains block 16A with NIF-filter

Rev. date: 2026-03-30

Customs tariff no: 8536901000

Country of origin: Sweden

### SUPRA Mains Block MD-16-EU

Supra LoRad MD mains blocks are designed to shield and filter noise. Supra NIF (Non-Intrusive Filtering), an efficient high frequency (RFI) transient filter. It is designed and configured to efficiently suppress RFI interference, but not to dampen quick recharge demands from the connected devices power supplies. Supra NIF is developed by Ben Duncan Research in England.sources. It is possible to order with custom configuration and have a capacity to suppress noise floor up to 40 dB! The Aluminum chassis is a very potent magnetic field insulation, why our mains block as well as adjacent devices is efficiently shielded from both electric, electro-magnetic and magnetic fields, a much wanted property where there is high currents rushing.


All parts are made in Sweden or Germany & assambled in our factory in Ljungskile, Sweden.

Cable not included!

- Noise reduction of up to 40 dB
- Internal wiring with 2.5 mm<sup>2</sup> oxygen-free copper conductors
- Supports peak power of 2400 W at 230 V / 10 A
- Protects both equipment and users from electrical interference
- Flexible installation: wall-mounted or freestanding (rubber feet and brackets included)
- Custom-designed NIF filter developed by Ben Duncan Research (UK)
- Shielded aluminum chassis to block electrical, electromagnetic, and magnetic interference

### CONSTRUCTION

Chassis:	Aluminum
Standard:	European Standard
Inlet socket:	SUPRA MCH-16, 16A
Outlet sockets:	7 to 11 x SUPRA MCH-16/EU, Schuko
Rated Current/Voltage:	16A / 250V / 3680W
Max RFI Noise damping:	40dB
Width & height (WxH):	90x50mm
Length (L):	MD07-EU = 837mm + 52mm for each additional socket
Standard filtering:	No NIF-filter for outlet no 1-2 Increased filtering, the last socket got highest damping



Note! 16A Inlet

All mains blocks can be ordered with or without filters for any of the sockets.

Power Amps are recommended to be connected to an unfiltered outlet.

Connect the Mains block with a LoRad cord set (16A) further reduce noise by 6-12 dB!



PRODUCT	Qty	Part no.	EAN-13	Carton	Weight
MAINS BLOCK MD07-16-EU	1PC	3024000394	7330060207020	10	1,51
MAINS BLOCK MD09-16-EU	1PC	3024000402	7330060207037	10	1,85