



SUPRA MAINS BLOCK MD-CH/SP

Screened Mains block 10 with surge protection & NIF-filter

Rev.date: 2026-04-16

Customs tariff no: 8536901000

Country of origin: Sweden

SUPRA Mains Block MD-CH (Swiss)

Supra LoRad MD mains blocks are designed to shield and filter noise and protect the electronic gear from surges. The NIF-filter (Non-Intrusive Filtering) is a mild RFI (Radio Frequency Interference) filter damping the high frequency noise from all sorts of modern household sources. It is possible to order with custom configuration and have a capacity to suppress noise floor up to 40 dB! The SP-models are all equipped with the Supra Surge Protection which protects all three ways; i.e. Live to Earth, Neutral to Earth and Live to Neutral. The standard surge protection manufacturer think that it is sufficient to offer only Live to Neutral protection, and they do not protect against field surges by proximate lightning strikes. The only better way to protect your equipment compared to Supra SP is to disconnect all mains power, interconnects and communications with adjacent devices completely.

Switch (optional), include also a high current in-rush capable on/off switch allowing for turning the entire equipment on or off. All parts are made in Sweden or Germany & assambled in our factory in Ljungskile, Sweden.

- SP three-way surge protection rejects close perimeter lightning & other surges
- Noise damping up to 40 dB!
- Internal wiring of 2.5 mm² oxygen-free copper leads
- Support a staggering peak power 2400 Watt @ 230 Volt and 10 Ampere
- Protect both you and your gear from various alternating fields and your gear from Surges
- Wall mounted or standing on a flat hard surface. Rubber feet and brackets included
- Custom tailored NIF-filter from Ben Duncan Research in UK
- Shielded aluminum chassis prevents electric, electro-magnetic and magnetic fields



Cable not included!



CONSTRUCTION

Chassis:	Aluminum
Standard:	Swiss Standard
Inlet socket:	SUPRA MCH-10, 10A
Outlet sockets:	2 to 6 x SUPRA MCH-16/CH, Schuko
Rated Current/Voltage:	10A / 250V / 2400W
Max RFI Noise damping:	40dB
Width & height (WxH):	90x50mm
Length (L):	MD06-CH = 164mm + 52mm for each additional socket
Standard filtering:	No NIF-filter for outlet no 1 for MD02-MD06. Increased filtering, the last socket got highest damping.



Note! 16A Inlet

All mains blocks can be ordered with or without filters for any of the sockets. Power Amps are recommended to be connected to an unfiltered outlet. Connect the Mains block with a LoRad cord set (10A) further reduce noise by 6-12 dB!



PRODUCT	Qty	Part no.	EAN-13	Carton	Weight
MAINS BLOCK MD06-CH/SP	1PC	3024000287	7330060205903	20	1,36
MAINS BLOCK MD06-CH/SP SWITCH	1PC	3024001046	7330060209802	20	1,45