



SUPRA MAINS BLOCK DC-16-BS/SP

Screened Mains block 16A with surge protection,
DC-blocker & NIF-filter

Rev.date: 2026-04-17

Customs tariff no: 8536901000

Country of origin: Sweden

SUPRA Mains Block MD-16-BS

Supra LoRad MD mains blocks are designed to shield and filter electrical noise while protecting connected equipment from power surges. Its advanced NIF (Non-Intrusive Filtering) and DC-blocker technology, developed in partnership with Ben Duncan Research (UK), reduce high-frequency interference from household devices, suppressing up to 40 dB of noise. This reduction prevents DC currents, caused by the increasing use of asymmetrically loaded devices, from compromising audio fidelity. The unit's DC-blocker stabilizes the power supply, eliminating hum and heat in sensitive Hifi equipment for optimal sound quality. Many conventional surge protection solutions only cover Live to Neutral and do not adequately protect against field-induced surges, such as those caused by nearby lightning strikes. For maximum protection, complete disconnection from mains power and all connected equipment remains the only superior safeguard.

All parts are made in Sweden or Germany & assembled in our factory in Ljungskile, Sweden.


- Noise damping up to 40 dB!
- Internal wiring of 2.5 mm² oxygen-free copper leads
- Support a staggering peak power 3750 Watt @ 230 Volt and 13 Ampere
- Protect both you and your gear from various alternating fields
- Wall mounted or standing on a flat hard surface. Rubber feet and brackets included
- Custom tailored NIF-filter from Ben Duncan Research in UK
- Shielded aluminum chassis prevents electric, electro-magnetic and magnetic fields

Cable not included!



CONSTRUCTION

Chassis:	Aluminum
Standard:	British Standard / BS approved 1363/A
Inlet socket:	SUPRA MCH-16, 16A
Outlet sockets:	6 x SUPRA MCH-13/BS
Rated Current/Voltage:	13A / 230V / 3750W
Max RFI Noise damping:	40dB
Width & height (WxH):	90x50mm
Length (L):	67mm + 52mm for each additional socket
Standard filtering:	No NIF-filter for outlet no 1. Increased filtering, the last socket got highest damping.



Note! 16A Inlet

All mains blocks can be ordered with or without filters for any of the sockets.

Power Amps are recommended to be connected to an unfiltered outlet.

Connect the Mains block with a LoRad cord set (16A) further reduce noise by 6-12 dB!



PRODUCT	Qty	Part no.	EAN-13	Carton	Weight
MAINS BLOCK MD06DC-16-BS/SP	1PC	Made upon request		10	1,75