

## SUPRA MAINS BLOCK MD-EU Switch

Screened Mains block with NIF-filter & Switch

Rev.date: 2026-03-25

Customs tariff no: 8536901000

Country of origin: Sweden



### SUPRA Mains Block MD-EU

Supra LoRad MD mains blocks are designed to shield and filter noise. Supra NIF (Non-Intrusive Filtering), an efficient high frequency (RFI) transient filter. It is designed and configured to efficiently suppress RFI interference, but not to dampen quick recharge demands from the connected devices power supplies. Supra NIF is developed by Ben Duncan Research in England.sources. It is possible to order with custom configuration and have a capacity to suppress noise floor up to 40 dB!

The switch versions also feature a high inrush-current capable on/off switch, allowing the entire system to be powered on or off simultaneously.

All parts are made in Sweden or Germany & assambled in our factory in Ljungskile, Sweden.

- Noise damping up to 40 dB!
- Internal wiring of 2.5 mm<sup>2</sup> oxygen-free copper leads
- Support a staggering peak power 2400 Watt @ 230 Volt and 10 Ampere
- Protect both you and your gear from various alternating fields
- Wall mounted or standing on a flat hard surface. Rubber feet and brackets included
- Custom tailored NIF-filter from Ben Duncan Research in UK
- Shielded aluminum chassis prevents electric, electro-magnetic and magnetic fields
- 2-pole On/Off Switch high inrush 20A

Cable not included!



### CONSTRUCTION

Chassis:	Aluminum
Standard:	European Standard
Inlet socket:	SUPRA MCH-10, 10A
Outlet sockets:	2 to 6 x SUPRA MCH-16/EU, Schuko
Rated Current/Voltage:	10A / 250V / 2400W
Max RFI Noise damping:	40dB
Switch:	2-polig On/Off 20A High inrush
Fuse:	Ceramic 10A, slow
Width & height (WxH):	90x50mm
Length (L):	MD03-EU = 216mm + 52mm for each additional socket
Standard filtering:	No filter on outlet no 1 for MD02-MD06 Increased filtering, the last socket got highest damping



All mains blocks can be ordered with or without filters for any of the sockets.  
Power Amps are recommended to be connected to an unfiltered outlet.



PRODUCT	Qty	Part no.	EAN-13	Carton	Weight
MAINS BLOCK MD02-EU SWITCH	1PC	3024001020	7330060209758	20	0,64
MAINS BLOCK MD03-EU SWITCH	1PC	3024000501	7330060207150	20	0,77
MAINS BLOCK MD06-EU SWITCH	1PC	3024000311	7330060205941	20	1,22