

SUPRA Y-LINK 1RCA-2RCA


Analogue Interconnect Active Speaker/Subwoofer

Gauge: 2x3x0.24mm² / AWG 23

Rev. date: 2026-06-10

Customs tariff no: 8544429010

Country of origin: Sweden



- Shielding – Highly effective suppression of external noise, RFI/EMI interference, and microphonic effects
- Easy to install – Flexible and slim cable design for straightforward installation, including in conduits
- Low capacitance – Ensures accurate bass reproduction, fast transient response, and minimal signal degradation
- Robust connectors – Precision-engineered 24K gold-plated connectors for low contact resistance and long-term reliability

Y-link 1RCA-2RCA Audio - Splits a single-channel subwoofer output into two mono inputs

The SUPRA Y-Link connects a receiver or amplifier with a single LFE/subwoofer output to an active subwoofer featuring dual RCA inputs, or to any application requiring one signal to feed two inputs. Many subwoofers achieve higher input sensitivity when both RCA inputs are connected. The Y-Link splits a single mono LFE signal into two identical mono outputs, ensuring optimal signal level and performance. The Y-Link does not create a stereo signal; it simply distributes one mono source signal to two mono inputs. Factory-terminated with high-quality SUPRA RCA-8SL and RCA-6 connectors featuring gold-plated contacts for low contact resistance and long-term reliability.

CONSTRUCTION

Cable	SUPRA Biline
Jacket:	PVC GA78, round
Diameter:	7.1mm
Colour:	Ice Blue & White (other colours upon request)
Marking:	SUPRA Biline > Made in Sweden > Meter mark
Screen connection:	Semi-balanaced, the screens are only connected in the source end
Connectors:	SUPRA RCA-8SL rca male & SUPRA RCA-6 male
- Type:	1 RCA Male > 2 RCA Male
- Material:	24K gold-plated copper alloy
- Colour:	Anthracite grey, Split Ice Blue: STRAIN RELIEF Y-SPLIT 8L60 BLUE
Solder tin:	Almit SR34 Super
Signal direction:	Follow the arrows printed on the cable > source > receiver
Packaging:	1-6M: 23x20x4cm, 8-10M: 23x20x6cm, 12-15M: 31x28x4.3cm

! RCA-8SL with chuck lock. Turn the grey housing to release or lock the plug to the female terminal.

▶ Release ◀ Lock



Special lengths are made upon request.



PRODUCT	Qty	Part.no	EAN-13	E-no	Crt Weight
Y-LINK 1RCA-2RCA BLUE 1M	1PC	1001910312	7330060210402	N/A	25 0,28
Y-LINK 1RCA-2RCA BLUE 2M	1PC	1001900586	7330060003516	6243067	25 0,32
Y-LINK 1RCA-2RCA BLUE 4M	1PC	1001900594	7330060003523	6243069	25 0,45
Y-LINK 1RCA-2RCA BLUE 6M	1PC	1001903218	7330060083044	6243071	25 0,60
Y-LINK 1RCA-2RCA BLUE 8M	1PC	1001900602	7330060003530	6243072	13 0,79
Y-LINK 1RCA-2RCA BLUE 10M	1PC	1001905882	7330060201745	6243061	13 0,91
Y-LINK 1RCA-2RCA BLUE 12M	1PC	1001905015	7330060200809	6243063	13 0,68
Y-LINK 1RCA-2RCA BLUE 15M	1PC	1001901394	7330060063886	6243065	13 1,07

PRODUCT	Qty	Part.no	EAN-13	Crt	Weight
Y-LINK 1RCA-2RCA WHITE 2M	1PC	1001907995	7330060204715	25	0,32
Y-LINK 1RCA-2RCA WHITE 3M	1PC	1001910106	7330060209918	25	0,40
Y-LINK 1RCA-2RCA WHITE 4M	1PC	1001908001	7330060204722	25	0,45
Y-LINK 1RCA-2RCA WHITE 5M	1PC	1001910114	7330060209925	25	0,50
Y-LINK 1RCA-2RCA WHITE 6M	1PC	1001908019	7330060204739	25	0,60
Y-LINK 1RCA-2RCA WHITE 8M	1PC	1001908027	7330060204746	13	0,79
Y-LINK 1RCA-2RCA WHITE 10M	1PC	1001907961	7330060204685	13	0,91
Y-LINK 1RCA-2RCA WHITE 12M	1PC	1001907979	7330060204692	13	0,68
Y-LINK 1RCA-2RCA WHITE 15M	1PC	1001907987	7330060204708	13	1,07