



SUPRA MAINS BLOCK MD-BS

Screened Mains block with NIF-filter

Rev.date: 2026-04-15

Customs tariff no: 8536901000

Country of origin: Sweden

SUPRA Mains Block MD-BS

Supra LoRad MD mains blocks are designed to shield and filter noise. Supra NIF (Non-Intrusive Filtering), an efficient high frequency (RFI) transient filter. It is designed and configured to efficiently suppress RFI interference, but not to dampen quick recharge demands from the connected devices power supplies. Supra NIF is developed by Ben Duncan Research in England.sources. It is possible to order with custom configuration and have a capacity to suppress noise floor up to 40 dB!

Switch (optional), include also a high current in-rush capable on/off switch allowing for turning the entire equipment on or off.

All parts are made in Sweden or Germany & assembled in our factory in Ljungs-kile, Sweden.


- Noise damping up to 40 dB!
- Internal wiring of 2.5 mm² oxygen-free copper leads
- Support a staggering peak power 3680 Watt @ 230 Volt and 16 Ampere
- Protect both you and your gear from various alternating fields
- Wall mounted or standing on a flat hard surface. Rubber feet and brackets included
- Custom tailored NIF-filter from Ben Duncan Research in UK
- Shielded aluminum chassis prevents electric, electro-magnetic and magnetic fields

Cable not included!



CONSTRUCTION

Chassis:	Aluminum
Standard:	British Standard / BS approved 1363/A
Inlet socket:	SUPRA MCH-16, 16A
Outlet sockets:	2 to 6 x SUPRA MCH-13/BS
Rated Current/Voltage:	16A / 250V / 3680W
Max RFI Noise damping:	40dB
Fuse:	-
Width & height (WxH):	90x50mm
Length (L):	MD02-BS = 164mm + 52mm for each additional socket
Standard filtering:	No filter on outlet no 1 for MD02-MD06 Increased filtering, the last socket got highest damping



Note! 16A Inlet

All mains blocks can be ordered with or without filters for any of the sockets.

Power Amps are recommended to be connected to an unfiltered outlet.

Connect the Mains block with a LoRad cord set (16A) further reduce noise by 6-12 dB!



PRODUCT	Qty	Part no.	EAN-13	Carton	Weight
MAINS BLOCK MD02-BS	1PCS	3024000428	7330060207167	20	0,63
MAINS BLOCK MD04-BS	1PCS	3024000519	7330060207181	20	0,89
MAINS BLOCK MD06-BS	1PCS	3024000535	7330060207204	20	1,21
MAINS BLOCK MD07-BS	1PCS	3024000568	7330060207242	20	1,69
MAINS BLOCK MD09-BS	1PCS	3024000444	7330060207211	10	1,69